

Schematics Page Index (Title / Revision / Change Date)

Vinafix

Page	Title of Schematics Page	Rev.	Date
01	Schematics Page Index	2.0	08/24
02	Block Diagram	2.0	08/24
03	Yonah(HOST BUS) 1/2	2.0	08/24
04	Yonah(HOST BUS) 2/3	2.0	08/24
05	Yonah(Power/Gnd) 3/3	2.0	08/24
06	CALISTOGA (HOST) 1/7	2.0	08/24
07	CALISTOG (DMI) 2/7	2.0	08/24
08	CALIST (GRAPHIC) 3/7	2.0	08/24
09	CALISTOGA (DDR2) 4/7	2.0	08/24
10	CALIST (POWER,VCC) 5/7	2.0	08/24
11	CALIST (VCC CORE) 6/7	2.0	08/24
12	CALIST (VSS) 7/7	2.0	08/24
13	DDR2(S0-DIMM_0) 1/3	2.0	08/24
14	DDR2(S0-DIMM_1) 2/3	2.0	08/24
15	DDR2(Termination) 3/3	2.0	08/24
16	LVDS	2.0	08/24
17	CRT	2.0	08/24
18	LAN CONTROLL	2.0	08/24
19	LAN TRANSFORMER	2.0	08/24
20	CLOCK GEN	2.0	08/24
21	ICH7-M(PCI/USB) 1/5	2.0	08/24
22	ICH7-M(LPC,IDE,SATA)2/5	2.0	08/24
23	ICH7-M(GPIO) 3/5	2.0	08/24
24	ICH7-M(POWER) 4/5	2.0	08/24
25	ICH7-M(GND) 5/5	2.0	08/24
26	SATA HDD/CD-ROM	2.0	08/24
27	EC+KBC	2.0	08/24
28	Flash ROM/X-Bus	2.0	08/24
29	LED/Touch PAD	2.0	08/24
30	Mini-PCIE Card	2.0	08/24
31	FAN	2.0	08/24
32	OIDE	2.0	08/24
33	AUDIO(CODEC & POWER)	2.0	08/24
34	AUDIO(AMP & HP & SPK)	2.0	08/24
35	AUDIO(EXTMIC)	2.0	08/24

Page	Title of Schematics Page	Rev.	Date
36	AUDIO (MUTE)	2.0	08/24
37	EXPRESS CARD/MDC	2.0	08/24
38	PCI (PCI BUS)	2.0	08/24
39	PCI (ILINK)	2.0	08/24
40	PCI (MS-DUO/MDC)	2.0	08/24
41	Button/LID Switch/EMI CAP	2.0	08/24
42	USB2.0	2.0	08/24
43	HOLE	2.0	08/24
44	Power Design Diagram	2.0	08/24
45	DCIN&Charger	2.0	08/24
46	SYS Power (+3_3V/+5V)	2.0	08/24
47	SYS Power(+1_5V/+1_05V)	2.0	08/24
48	DDR2 Power(+1_8V/+0_9V)	2.0	08/24
49	CPU_Vcore ---MAX8771	2.0	08/24
50	Others power plan	2.0	08/24
51	OVP protection	2.0	08/24
52	History (1)	2.0	08/24
53	History (2)	2.0	08/24
54			
55			
56			
57			
58			
59			
60			

P. Leader	Check by	Design by


Project Code & Schematics Subject: MS70 Main Board


PCB P/N: (FUBAI) 1P-0068100-6011
(NAN YA) 1P-0068200-6011
(HANSTAR) 1P-0068500-6011

FOXCONN		HON HAI Precision Ind. Co., Ltd. CCPBG - R&D Division	
Title Index Page			
Size A3	Document Number MS70-1-01	Rev 2.0	
Date: Tuesday, August 22, 2006	Sheet 1	of 55	

www.vinafix.vn

RAPTOR/MS70(CALISTOGA GM/GML Block Diagram)







Layout note:
no stub on
H_STPCLK#



A#[32-39], APM#[0-1]:
Leave escape routing
on for future
functionality

ICH7M's GPIO12: VIL----> -0.5V ~ -0.8V
VIH----> 2.0V ~ 3.3+0.5V
YONAH's PROCHOT#: VIL----> -0.1V ~ -0.3*VCCP
VIH----> 0.7*VCCP ~ VCCP+0.1








PM_THRMTRIP#
should connect to
ICH7-M and GMCH
without T-ing (No
stub)









CPU_VCCA---->120mA
 CPU_VCCP----->2.5A
 CPU_VCC----->36A






Place close to chipset









- Pin list for CALISTOGA (VCC pins):
- AA33 VCC_0
 - W33 VCC_1
 - P33 VCC_2
 - L33 VCC_3
 - J33 VCC_4
 - AA32 VCC_5
 - Y32 VCC_6
 - Y32 VCC_7
 - Y32 VCC_8
 - P32 VCC_9
 - N32 VCC_10
 - M32 VCC_11
 - L32 VCC_12
 - J32 VCC_13
 - AA31 VCC_14
 - W31 VCC_15
 - V31 VCC_16
 - T31 VCC_17
 - R31 VCC_18
 - P31 VCC_19
 - N31 VCC_20
 - M31 VCC_21
 - W30 VCC_22
 - V30 VCC_23
 - T30 VCC_24
 - R30 VCC_25
 - P30 VCC_26
 - N30 VCC_27
 - M30 VCC_28
 - L30 VCC_29
 - AA29 VCC_30
 - Y29 VCC_31
 - Y29 VCC_32
 - Y29 VCC_33
 - Y29 VCC_34
 - Y29 VCC_35
 - Y29 VCC_36
 - Y29 VCC_37
 - Y29 VCC_38
 - Y29 VCC_39
 - Y29 VCC_40
 - Y29 VCC_41
 - Y29 VCC_42
 - Y29 VCC_43
 - Y29 VCC_44
 - Y28 VCC_45
 - Y28 VCC_46
 - Y28 VCC_47
 - Y28 VCC_48
 - Y28 VCC_49
 - Y28 VCC_50
 - Y28 VCC_51
 - Y28 VCC_52
 - Y28 VCC_53
 - Y28 VCC_54
 - Y28 VCC_55
 - Y28 VCC_56
 - Y28 VCC_57
 - Y28 VCC_58
 - Y28 VCC_59
 - Y28 VCC_60
 - Y28 VCC_61
 - Y28 VCC_62
 - Y28 VCC_63
 - Y28 VCC_64
 - Y28 VCC_65
 - Y28 VCC_66
 - Y28 VCC_67
 - Y28 VCC_68
 - Y28 VCC_69
 - Y28 VCC_70
 - Y28 VCC_71
 - Y28 VCC_72
 - Y28 VCC_73
 - Y28 VCC_74
 - Y28 VCC_75
 - Y28 VCC_76
 - Y28 VCC_77
 - Y28 VCC_78
 - Y28 VCC_79
 - Y28 VCC_80
 - Y28 VCC_81
 - Y28 VCC_82
 - Y28 VCC_83
 - Y28 VCC_84
 - Y28 VCC_85
 - Y28 VCC_86
 - Y28 VCC_87
 - Y28 VCC_88
 - Y28 VCC_89
 - Y28 VCC_90
 - Y28 VCC_91
 - Y28 VCC_92
 - Y28 VCC_93
 - Y28 VCC_94
 - Y28 VCC_95
 - Y28 VCC_96
 - Y28 VCC_97
 - Y28 VCC_98
 - Y28 VCC_99
 - Y28 VCC_100
 - Y28 VCC_101
 - Y28 VCC_102
 - Y28 VCC_103
 - Y28 VCC_104
 - Y28 VCC_105
 - Y28 VCC_106
 - Y28 VCC_107
 - Y28 VCC_108
 - Y28 VCC_109
 - Y28 VCC_110

VCC



- Pin list for CALISTOGA (VCCSSM pins):
- AU41 VCCSSM_0
 - AT41 VCCSSM_1
 - AM41 VCCSSM_2
 - AM40 VCCSSM_3
 - AX34 VCCSSM_4
 - AW34 VCCSSM_5
 - AV34 VCCSSM_6
 - AT34 VCCSSM_7
 - AT34 VCCSSM_8
 - AT34 VCCSSM_9
 - BA30 VCCSSM_10
 - AY30 VCCSSM_11
 - AW30 VCCSSM_12
 - AV30 VCCSSM_13
 - AT30 VCCSSM_14
 - AT30 VCCSSM_15
 - AR30 VCCSSM_16
 - AP30 VCCSSM_17
 - AN30 VCCSSM_18
 - AM29 VCCSSM_19
 - AL29 VCCSSM_20
 - AK29 VCCSSM_21
 - AJ29 VCCSSM_22
 - AH29 VCCSSM_23
 - AJ28 VCCSSM_24
 - AH28 VCCSSM_25
 - AJ27 VCCSSM_26
 - AH27 VCCSSM_27
 - BA26 VCCSSM_28
 - AX26 VCCSSM_29
 - AW26 VCCSSM_30
 - AT26 VCCSSM_31
 - AT26 VCCSSM_32
 - AT26 VCCSSM_33
 - AT26 VCCSSM_34
 - AT26 VCCSSM_35
 - AT26 VCCSSM_36
 - AT26 VCCSSM_37
 - AT26 VCCSSM_38
 - AT26 VCCSSM_39
 - AT26 VCCSSM_40
 - AT26 VCCSSM_41
 - AT26 VCCSSM_42
 - AT26 VCCSSM_43
 - AT26 VCCSSM_44
 - AT26 VCCSSM_45
 - AT26 VCCSSM_46
 - AT26 VCCSSM_47
 - AT26 VCCSSM_48
 - AT26 VCCSSM_49
 - AT26 VCCSSM_50
 - AT26 VCCSSM_51
 - AT26 VCCSSM_52
 - AT26 VCCSSM_53
 - AT26 VCCSSM_54
 - AT26 VCCSSM_55
 - AT26 VCCSSM_56
 - AT26 VCCSSM_57
 - AT26 VCCSSM_58
 - AT26 VCCSSM_59
 - AT26 VCCSSM_60
 - AT26 VCCSSM_61
 - AT26 VCCSSM_62
 - AT26 VCCSSM_63
 - AT26 VCCSSM_64
 - AT26 VCCSSM_65
 - AT26 VCCSSM_66
 - AT26 VCCSSM_67
 - AT26 VCCSSM_68
 - AT26 VCCSSM_69
 - AT26 VCCSSM_70
 - AT26 VCCSSM_71
 - AT26 VCCSSM_72
 - AT26 VCCSSM_73
 - AT26 VCCSSM_74
 - AT26 VCCSSM_75
 - AT26 VCCSSM_76
 - AT26 VCCSSM_77
 - AT26 VCCSSM_78
 - AT26 VCCSSM_79
 - AT26 VCCSSM_80
 - AT26 VCCSSM_81
 - AT26 VCCSSM_82
 - AT26 VCCSSM_83
 - AT26 VCCSSM_84
 - AT26 VCCSSM_85
 - AT26 VCCSSM_86
 - AT26 VCCSSM_87
 - AT26 VCCSSM_88
 - AT26 VCCSSM_89
 - AT26 VCCSSM_90
 - AT26 VCCSSM_91
 - AT26 VCCSSM_92
 - AT26 VCCSSM_93
 - AT26 VCCSSM_94
 - AT26 VCCSSM_95
 - AT26 VCCSSM_96
 - AT26 VCCSSM_97
 - AT26 VCCSSM_98
 - AT26 VCCSSM_99
 - AT26 VCCSSM_100
 - AT26 VCCSSM_101
 - AT26 VCCSSM_102
 - AT26 VCCSSM_103
 - AT26 VCCSSM_104
 - AT26 VCCSSM_105
 - AT26 VCCSSM_106
 - AT26 VCCSSM_107



- Pin list for CALISTOGA (VCCSSM pins):
- AD27 VCC_NCTF0
 - AB27 VCC_NCTF1
 - AB27 VCC_NCTF2
 - Y27 VCC_NCTF3
 - W27 VCC_NCTF4
 - V27 VCC_NCTF5
 - U27 VCC_NCTF6
 - T27 VCC_NCTF7
 - R27 VCC_NCTF8
 - AD26 VCC_NCTF9
 - AC26 VCC_NCTF10
 - AB26 VCC_NCTF11
 - AA26 VCC_NCTF12
 - Y26 VCC_NCTF13
 - W26 VCC_NCTF14
 - V26 VCC_NCTF15
 - U26 VCC_NCTF16
 - T26 VCC_NCTF17
 - R26 VCC_NCTF18
 - AD25 VCC_NCTF19
 - AC25 VCC_NCTF20
 - AB25 VCC_NCTF21
 - AA25 VCC_NCTF22
 - Y25 VCC_NCTF23
 - W25 VCC_NCTF24
 - V25 VCC_NCTF25
 - U25 VCC_NCTF26
 - T25 VCC_NCTF27
 - R25 VCC_NCTF28
 - AD24 VCC_NCTF29
 - AC24 VCC_NCTF30
 - AB24 VCC_NCTF31
 - AA24 VCC_NCTF32
 - Y24 VCC_NCTF33
 - W24 VCC_NCTF34
 - V24 VCC_NCTF35
 - U24 VCC_NCTF36
 - T24 VCC_NCTF37
 - R24 VCC_NCTF38
 - AD23 VCC_NCTF39
 - AC23 VCC_NCTF40
 - AB23 VCC_NCTF41
 - AA23 VCC_NCTF42
 - Y23 VCC_NCTF43
 - W23 VCC_NCTF44
 - V23 VCC_NCTF45
 - U23 VCC_NCTF46
 - T23 VCC_NCTF47
 - R23 VCC_NCTF48
 - AD22 VCC_NCTF49
 - AC22 VCC_NCTF50
 - AB22 VCC_NCTF51
 - AA22 VCC_NCTF52
 - Y22 VCC_NCTF53
 - W22 VCC_NCTF54
 - V22 VCC_NCTF55
 - U22 VCC_NCTF56
 - T22 VCC_NCTF57
 - R22 VCC_NCTF58
 - AD21 VCC_NCTF59
 - AC21 VCC_NCTF60
 - AB21 VCC_NCTF61
 - AA21 VCC_NCTF62
 - Y21 VCC_NCTF63
 - W21 VCC_NCTF64
 - V21 VCC_NCTF65
 - U21 VCC_NCTF66
 - T21 VCC_NCTF67
 - R21 VCC_NCTF68
 - AD20 VCC_NCTF69
 - AC20 VCC_NCTF70
 - AB20 VCC_NCTF71
 - AA20 VCC_NCTF72
 - Y20 VCC_NCTF73
 - W20 VCC_NCTF74
 - V20 VCC_NCTF75
 - U20 VCC_NCTF76
 - T20 VCC_NCTF77
 - R20 VCC_NCTF78
 - AD19 VCC_NCTF79
 - AC19 VCC_NCTF80
 - AB19 VCC_NCTF81
 - AA19 VCC_NCTF82
 - Y19 VCC_NCTF83
 - W19 VCC_NCTF84
 - V19 VCC_NCTF85
 - U19 VCC_NCTF86
 - T19 VCC_NCTF87
 - R19 VCC_NCTF88
 - AD18 VCC_NCTF89
 - AC18 VCC_NCTF90
 - AB18 VCC_NCTF91
 - AA18 VCC_NCTF92
 - Y18 VCC_NCTF93
 - W18 VCC_NCTF94
 - V18 VCC_NCTF95
 - U18 VCC_NCTF96
 - T18 VCC_NCTF97
 - R18 VCC_NCTF98
 - AD17 VCC_NCTF99
 - AC17 VCC_NCTF100
 - AB17 VCC_NCTF101
 - AA17 VCC_NCTF102
 - Y17 VCC_NCTF103
 - W17 VCC_NCTF104
 - V17 VCC_NCTF105
 - U17 VCC_NCTF106
 - T17 VCC_NCTF107
 - R17 VCC_NCTF108
 - AD16 VCC_NCTF109
 - AC16 VCC_NCTF110
 - AB16 VCC_NCTF111
 - AA16 VCC_NCTF112
 - Y16 VCC_NCTF113
 - W16 VCC_NCTF114
 - V16 VCC_NCTF115
 - U16 VCC_NCTF116
 - T16 VCC_NCTF117
 - R16 VCC_NCTF118
 - AD15 VCC_NCTF119
 - AC15 VCC_NCTF120
 - AB15 VCC_NCTF121
 - AA15 VCC_NCTF122
 - Y15 VCC_NCTF123
 - W15 VCC_NCTF124
 - V15 VCC_NCTF125
 - U15 VCC_NCTF126
 - T15 VCC_NCTF127
 - R15 VCC_NCTF128
 - AD14 VCC_NCTF129
 - AC14 VCC_NCTF130
 - AB14 VCC_NCTF131
 - AA14 VCC_NCTF132
 - Y14 VCC_NCTF133
 - W14 VCC_NCTF134
 - V14 VCC_NCTF135
 - U14 VCC_NCTF136
 - T14 VCC_NCTF137
 - R14 VCC_NCTF138
 - AD13 VCC_NCTF139
 - AC13 VCC_NCTF140
 - AB13 VCC_NCTF141
 - AA13 VCC_NCTF142
 - Y13 VCC_NCTF143
 - W13 VCC_NCTF144
 - V13 VCC_NCTF145
 - U13 VCC_NCTF146
 - T13 VCC_NCTF147
 - R13 VCC_NCTF148
 - AD12 VCC_NCTF149
 - AC12 VCC_NCTF150
 - AB12 VCC_NCTF151
 - AA12 VCC_NCTF152
 - Y12 VCC_NCTF153
 - W12 VCC_NCTF154
 - V12 VCC_NCTF155
 - U12 VCC_NCTF156
 - T12 VCC_NCTF157
 - R12 VCC_NCTF158
 - AD11 VCC_NCTF159
 - AC11 VCC_NCTF160
 - AB11 VCC_NCTF161
 - AA11 VCC_NCTF162
 - Y11 VCC_NCTF163
 - W11 VCC_NCTF164
 - V11 VCC_NCTF165
 - U11 VCC_NCTF166
 - T11 VCC_NCTF167
 - R11 VCC_NCTF168
 - AD10 VCC_NCTF169
 - AC10 VCC_NCTF170
 - AB10 VCC_NCTF171
 - AA10 VCC_NCTF172
 - Y10 VCC_NCTF173
 - W10 VCC_NCTF174
 - V10 VCC_NCTF175
 - U10 VCC_NCTF176
 - T10 VCC_NCTF177
 - R10 VCC_NCTF178
 - AD9 VCC_NCTF179
 - AC9 VCC_NCTF180
 - AB9 VCC_NCTF181
 - AA9 VCC_NCTF182
 - Y9 VCC_NCTF183
 - W9 VCC_NCTF184
 - V9 VCC_NCTF185
 - U9 VCC_NCTF186
 - T9 VCC_NCTF187
 - R9 VCC_NCTF188
 - AD8 VCC_NCTF189
 - AC8 VCC_NCTF190
 - AB8 VCC_NCTF191
 - AA8 VCC_NCTF192
 - Y8 VCC_NCTF193
 - W8 VCC_NCTF194
 - V8 VCC_NCTF195
 - U8 VCC_NCTF196
 - T8 VCC_NCTF197
 - R8 VCC_NCTF198
 - AD7 VCC_NCTF199
 - AC7 VCC_NCTF200
 - AB7 VCC_NCTF201
 - AA7 VCC_NCTF202
 - Y7 VCC_NCTF203
 - W7 VCC_NCTF204
 - V7 VCC_NCTF205
 - U7 VCC_NCTF206
 - T7 VCC_NCTF207
 - R7 VCC_NCTF208
 - AD6 VCC_NCTF209
 - AC6 VCC_NCTF210
 - AB6 VCC_NCTF211
 - AA6 VCC_NCTF212
 - Y6 VCC_NCTF213
 - W6 VCC_NCTF214
 - V6 VCC_NCTF215
 - U6 VCC_NCTF216
 - T6 VCC_NCTF217
 - R6 VCC_NCTF218
 - AD5 VCC_NCTF219
 - AC5 VCC_NCTF220
 - AB5 VCC_NCTF221
 - AA5 VCC_NCTF222
 - Y5 VCC_NCTF223
 - W5 VCC_NCTF224
 - V5 VCC_NCTF225
 - U5 VCC_NCTF226
 - T5 VCC_NCTF227
 - R5 VCC_NCTF228
 - AD4 VCC_NCTF229
 - AC4 VCC_NCTF230
 - AB4 VCC_NCTF231
 - AA4 VCC_NCTF232
 - Y4 VCC_NCTF233
 - W4 VCC_NCTF234
 - V4 VCC_NCTF235
 - U4 VCC_NCTF236
 - T4 VCC_NCTF237
 - R4 VCC_NCTF238
 - AD3 VCC_NCTF239
 - AC3 VCC_NCTF240
 - AB3 VCC_NCTF241
 - AA3 VCC_NCTF242
 - Y3 VCC_NCTF243
 - W3 VCC_NCTF244
 - V3 VCC_NCTF245
 - U3 VCC_NCTF246
 - T3 VCC_NCTF247
 - R3 VCC_NCTF248
 - AD2 VCC_NCTF249
 - AC2 VCC_NCTF250
 - AB2 VCC_NCTF251
 - AA2 VCC_NCTF252
 - Y2 VCC_NCTF253
 - W2 VCC_NCTF254
 - V2 VCC_NCTF255
 - U2 VCC_NCTF256
 - T2 VCC_NCTF257
 - R2 VCC_NCTF258
 - AD1 VCC_NCTF259
 - AC1 VCC_NCTF260
 - AB1 VCC_NCTF261
 - AA1 VCC_NCTF262
 - Y1 VCC_NCTF263
 - W1 VCC_NCTF264
 - V1 VCC_NCTF265
 - U1 VCC_NCTF266
 - T1 VCC_NCTF267
 - R1 VCC_NCTF268
 - AD0 VCC_NCTF269
 - AC0 VCC_NCTF270
 - AB0 VCC_NCTF271
 - AA0 VCC_NCTF272
 - Y0 VCC_NCTF273
 - W0 VCC_NCTF274
 - V0 VCC_NCTF275
 - U0 VCC_NCTF276
 - T0 VCC_NCTF277
 - R0 VCC_NCTF278
 - AD27 VCC_NCTF279
 - AB27 VCC_NCTF280
 - Y27 VCC_NCTF281
 - W27 VCC_NCTF282
 - V27 VCC_NCTF283
 - U27 VCC_NCTF284
 - T27 VCC_NCTF285
 - R27 VCC_NCTF286
 - AD26 VCC_NCTF287
 - AC26 VCC_NCTF288
 - AB26 VCC_NCTF289
 - AA26 VCC_NCTF290
 - Y26 VCC_NCTF291
 - W26 VCC_NCTF292
 - V26 VCC_NCTF293
 - U26 VCC_NCTF294
 - T26 VCC_NCTF295
 - R26 VCC_NCTF296
 - AD25 VCC_NCTF297
 - AC25 VCC_NCTF298
 - AB25 VCC_NCTF299
 - AA25 VCC_NCTF300
 - Y25 VCC_NCTF301
 - W25 VCC_NCTF302
 - V25 VCC_NCTF303
 - U25 VCC_NCTF304
 - T25 VCC_NCTF305
 - R25 VCC_NCTF306
 - AD24 VCC_NCTF307
 - AC24 VCC_NCTF308
 - AB24 VCC_NCTF309
 - AA24 VCC_NCTF310
 - Y24 VCC_NCTF311
 - W24 VCC_NCTF312
 - V24 VCC_NCTF313
 - U24 VCC_NCTF314
 - T24 VCC_NCTF315
 - R24 VCC_NCTF316
 - AD23 VCC_NCTF317
 - AC23 VCC_NCTF318
 - AB23 VCC_NCTF319
 - AA23 VCC_NCTF320
 - Y23 VCC_NCTF321
 - W23 VCC_NCTF322
 - V23 VCC_NCTF323
 - U23 VCC_NCTF324
 - T23 VCC_NCTF325
 - R23 VCC_NCTF326
 - AD22 VCC_NCTF327
 - AC22 VCC_NCTF328
 - AB22 VCC_NCTF329
 - AA22 VCC_NCTF330
 - Y22 VCC_NCTF331
 - W22 VCC_NCTF332
 - V22 VCC_NCTF333
 - U22 VCC_NCTF334
 - T22 VCC_NCTF335
 - R22 VCC_NCTF336
 - AD21 VCC_NCTF337
 - AC21 VCC_NCTF338
 - AB21 VCC_NCTF339
 - AA21 VCC_NCTF340
 - Y21 VCC_NCTF341
 - W21 VCC_NCTF342
 - V21 VCC_NCTF343
 - U21 VCC_NCTF344
 - T21 VCC_NCTF345
 - R21 VCC_NCTF346
 - AD20 VCC_NCTF347
 - AC20 VCC_NCTF348
 - AB20 VCC_NCTF349
 - AA20 VCC_NCTF350
 - Y20 VCC_NCTF351
 - W20 VCC_NCTF352
 - V20 VCC_NCTF353
 - U20 VCC_NCTF354
 - T20 VCC_NCTF355
 - R20 VCC_NCTF356
 - AD19 VCC_NCTF357
 - AC19 VCC_NCTF358
 - AB19 VCC_NCTF359
 - AA19 VCC_NCTF360
 - Y19 VCC_NCTF361
 - W19 VCC_NCTF362
 - V19 VCC_NCTF363
 - U19 VCC_NCTF364
 - T19 VCC_NCTF365
 - R19 VCC_NCTF366
 - AD18 VCC_NCTF367
 - AC18 VCC_NCTF368
 - AB18 VCC_NCTF369
 - AA18 VCC_NCTF370
 - Y18 VCC_NCTF371
 - W18 VCC_NCTF372
 - V18 VCC_NCTF373
 - U18 VCC_NCTF374
 - T18 VCC_NCTF375
 - R18 VCC_NCTF376
 - AD17 VCC_NCTF377
 - AC17 VCC_NCTF378
 - AB17 VCC_NCTF379
 - AA17 VCC_NCTF380
 - Y17 VCC_NCTF381
 - W17 VCC_NCTF382
 - V17 VCC_NCTF383
 - U17 VCC_NCTF384
 - T17 VCC_NCTF385
 - R17 VCC_NCTF386
 - AD16 VCC_NCTF387
 - AC16 VCC_NCTF388
 - AB16 VCC_NCTF389
 - AA16 VCC_NCTF390
 - Y16 VCC_NCTF391
 - W16 VCC_NCTF392
 - V16 VCC_NCTF393
 - U16 VCC_NCTF394
 - T16 VCC_NCTF395
 - R16 VCC_NCTF396
 - AD15 VCC_NCTF397
 - AC15 VCC_NCTF398
 - AB15 VCC_NCTF399
 - AA15 VCC_NCTF400
 - Y15 VCC_NCTF401
 - W15 VCC_NCTF402
 - V15 VCC_NCTF403
 - U15 VCC_NCTF404
 - T15 VCC_NCTF405
 - R15 VCC_NCTF406
 - AD14 VCC_NCTF407
 - AC14 VCC_NCTF408
 - AB14 VCC_NCTF409
 - AA14 VCC_NCTF410
 - Y14 VCC_NCTF411
 - W14 VCC_NCTF412
 - V14 VCC_NCTF413
 - U14 VCC_NCTF414
 - T14 VCC_NCTF415
 - R14 VCC_NCTF416
 - AD13 VCC_NCTF417
 - AC13 VCC_NCTF418
 - AB13 VCC_NCTF419
 - AA13 VCC_NCTF420
 - Y13 VCC_NCTF421
 - W13 VCC_NCTF422
 - V13 VCC_NCTF423
 - U13 VCC_NCTF424
 - T13 VCC_NCTF425
 - R13 VCC_NCTF426
 - AD12 VCC_NCTF427
 - AC12 VCC_NCTF428
 - AB12 VCC_NCTF429
 - AA12 VCC_NCTF430
 - Y12 VCC_NCTF431
 - W12 VCC_NCTF432
 - V12 VCC_NCTF433
 - U12 VCC_NCTF434
 - T12 VCC_NCTF435
 - R12 VCC_NCTF436
 - AD11 VCC_NCTF437
 - AC11 VCC_NCTF438
 - AB11 VCC_NCTF439
 - AA11 VCC_NCTF440
 - Y11 VCC_NCTF441
 - W11 VCC_NCTF442
 - V11 VCC_NCTF443
 - U11 VCC_NCTF444
 - T11 VCC_NCTF445
 - R11 VCC_NCTF446
 - AD10 VCC_NCTF447
 - AC10 VCC_NCTF448
 - AB10 VCC_NCTF449
 - AA10 VCC_NCTF450
 - Y10 VCC_NCTF451
 - W10 VCC_NCTF452
 - V10 VCC_NCTF453
 - U10 VCC_NCTF454
 - T10 VCC_NCTF455
 - R10 VCC_NCTF456
 - AD9 VCC_NCTF457
 - AC9 VCC_NCTF458
 - AB9 VCC_NCTF459
 - AA9 VCC_NCTF460
 - Y9 VCC_NCTF461
 - W9 VCC_NCTF462
 - V9 VCC_NCTF463
 - U9 VCC_NCTF464
 - T9 VCC_NCTF465
 - R9 VCC_NCTF466
 - AD8 VCC_NCTF467
 - AC8 VCC_NCTF468
 - AB8 VCC_NCTF469
 - AA8 VCC_NCTF470
 - Y8 VCC_NCTF471
 - W8 VCC_NCTF472
 - V8 VCC_NCTF473
 - U8 VCC_NCTF474
 - T8 VCC_NCTF475
 - R8 VCC_NCTF476
 - AD7 VCC_NCTF477
 - AC7 VCC_NCTF478
 - AB7 VCC_NCTF479
 - AA7 VCC_NCTF480
 - Y7 VCC_NCTF481
 - W7 VCC_NCTF482
 - V7 VCC_NCTF483
 - U7 VCC_NCTF484
 - T7 VCC_NCTF485
 - R7 VCC_NCTF486
 - AD6 VCC_NCTF487
 - AC6 VCC_NCTF488
 - AB6 VCC_NCTF489
 - AA6 VCC_NCTF490
 - Y6 VCC_NCTF491
 - W6 VCC_NCTF492
 - V6 VCC_NCTF493
 - U6 VCC_NCTF494
 - T6 VCC_NCTF495
 - R6 VCC_NCTF496
 - AD5 VCC_NCTF497
 - AC5 VCC_NCTF498
 - AB5 VCC_NCTF499
 - AA5 VCC_NCTF500
 - Y5 VCC_NCTF501
 - W5 VCC_NCTF502
 - V5 VCC_NCTF503
 - U5 VCC_NCTF504
 - T5 VCC_NCTF505
 - R5 VCC_NCTF506
 - AD4 VCC_NCTF507
 - AC4 VCC_NCTF508
 - AB4 VCC_NCTF509
 - AA4 VCC_NCTF510
 - Y4 VCC_NCTF511
 - W4 VCC_NCTF512
 - V4 VCC_NCTF513
 - U4 VCC_NCTF514
 - T4 VCC_NCTF515
 - R4 VCC_NCTF516
 - AD3 VCC_NCTF517
 - AC3 VCC_NCTF518
 - AB3 VCC_NCTF519
 - AA3 VCC_NCTF520
 - Y3 VCC_NCTF521
 - W3 VCC_NCTF522
 - V3 VCC_NCTF523
 - U3 VCC_NCTF524
 - T3 VCC_NCTF525
 - R3 VCC_NCTF526
 - AD2 VCC_NCTF527
 - AC2 VCC_NCTF528
 - AB2 VCC_NCTF529
 - AA2 VCC_NCTF530
 - Y2 VCC_NCTF531
 - W2 VCC_NCTF532
 - V2 VCC_NCTF533
 - U2 VCC_NCTF534
 - T2 VCC_NCTF535
 - R2 VCC_NCTF536
 - AD1 VCC_NCTF537
 - AC1 VCC_NCTF538
 - AB1 VCC_NCTF539
 - AA1 VCC_NCTF540
 - Y1 VCC_NCTF541
 - W1 VCC_NCTF542
 - V1 VCC_NCTF543
 - U1 VCC_NCTF544
 - T1 VCC_NCTF545
 - R1 VCC_NCTF546
 - AD0 VCC_NCTF547
 - AC0 VCC_NCTF548
 - AB0 VCC_NCTF549
 - AA0 VCC_NCTF550
 - Y0 VCC_NCTF551
 - W0 VCC_NCTF552
 - V0 VCC_NCTF553
 - U0 VCC_NCTF55

7 MCH_CFG_5 30MIL TP76

MCH_CFG_5
Low = DMIX2
High = DMIX4

MCH_CFG_18
(VCC_CORE Select)
Low = 1.05V(default)
High = 1.5V

7 MCH_CFG_18 30MIL TP79

7 MCH_CFG_6 30MIL TP77

MCH_CFG_6
Low = Moby Dick
High = Calistoga
DDR2 select (default high)

MCH_CFG_19
(DMI LANE REVERSAL)
Low = Normal(default)
High = LANES REVERSED

7 MCH_CFG_19 30MIL TP80

7 MCH_CFG_7 30MIL TP78

MCH_CFG_7
(CPU Strap)
Low = RSVD
High = Mobile Yonah processor

MCH_CFG_20
(PCIe Backward Interoperability mode)
Low = Only SDVO or PCIe x1 is operational (defaults)
High = SDVO and PCIe x1 are operating simultaneously via the PEG port

7 MCH_CFG_20 30MIL TP83

7 MCH_CFG_9 30MIL TP81

MCH_CFG_9
(PCIe Graphics Lane)
Low = Reverse Lane
High = Normal operation

For layout convenience

7 MCH_CFG_10 30MIL TP82

MCH_CFG_10
(HOST PLL VCC SELECT)
Low = RESERVED
High = MOBILITY

Layout Noe:
Location of all MCH_CFG strap resistors needs to be close to trace to minimize stub

7 MCH_CFG_11 30MIL TP84

MCH_CFG_11
(PSB 4x CLK ENABLE)
Low = Calistoga
High = Reserved

R93
NC_2.2K_J
0402



7 MCH_CFG_12 30MIL TP84

7 MCH_CFG_13 30MIL TP85

MCH_CFG [13:12]
(XOR/ALLZ)
00=Partial Clock Gating Disable
01=XOR Mode Enable
10=All-Z Mode Enable
11=Normal Operation(Default)


7 MCH_CFG_16 30MIL TP160

MCH_CFG_16
(FSB Dynamic ODT)
Low = Dynamic ODT Disabled
High = Dynamic ODT Enable






VSS






CALISTOGA




1.8V per DIMM=3.08A




PC2-4200/PC2-5300 DDR2 SDRAM SO-DIMM (200P)




SMBus Address: A0(W)/A1(R)



1.8V per DIMM=3.08A



PC2-4200/PC2-5300 DDR2 SDRAM SO-DIMM (200P)




FOXCONN		HON HAI Precision Ind. Co., Ltd.	
Title		CCPBG - R&D Division	
DDR(II)SO-DIMM_1			
Size A3	Document Number MS70-1-01		Rev 2.0
Date:	Tuesday, August 22, 2006	Sheet	14 of 55

www.vinafix.vn

48,50,51


+0_9VSUS












Layout note: Place 1 cap close to every 1 R-pack terminated to +0_9VSUS

48,50,51


+0_9VSUS




Layout note: Place 1 cap close to every 1 R-pack terminated to +0_9VSUS




LVDS




LVDS CONNECTOR DVT



INVERTER CONNECTOR




PANEL ID



PVT

Type	WXGA	WXGA	WSXGA
Size	15.4" wide	15.4" wide	15.4" wide
Vendor	CPT	QDI	InnoLux
Device Name	CLAA154WA05AN	QDI15TL0703	TBD
Panel ID Check[3..0]	1001	1010	1011


ON=0




DISCHARGE

The R461 will consume about 0.054 Watt ($3.3 \times 3.3 / 200 = 0.054W$). We changed resistor to 0603 size (1/8 Watt)

FOXCONN HON HAI Precision Ind. Co., Ltd. CCPBG - R&D Division		
Title LVDS		
Size A3	Document Number MS70-1-01	Rev 2.0
Date: Tuesday, August 22, 2006	Sheet 16	of 55




For EMI used







CRT CONNECTOR





DVT




DVT



FOXCONN HON HAI Precision Ind. Co., Ltd.		
CCPBG - R&D Division		
Title	CRT	
Size	Document Number	Rev
A3	MS70-1-01	2.0
Date:	Tuesday, August 22, 2006	Sheet 17 of 55






NC_10P_50V_E_N	2	1	CLK CB48
NC_10P_50V_E_N	2	1	CLK USB48
NC_10P_50V_E_N	2	1	CLK KBCPCI
NC_10P_50V_E_N	2	1	PCLK CB
NC_10P_50V_E_N	2	1	PCLK FW
NC_10P_50V_E_N	2	1	CLK ICHPCI
NC_10P_50V_E_N	2	1	CLK ICH14
NC_10P_50V_E_N	2	1	PCLK JIG
NC_10P_50V_E_N	2	1	C271 0402

close to clk gen (For EMI)

Length as short as possible.





Pin Straps	
Pin	Signal
pin53	pin 11/12
0	SRCCLK0
1	27MHz (v)
pin59	pin 15/16
0	SRCCLK0
1	SATA (v)
pin60	pin 37/38
0	SRCCLK8 (v)
1	CPU 2 ITP
pin64	pin 13/14
0	LCDCLK_SS (CA)
1	SRCCLK1 (NV)

FSB Frequency Table:


FSLB	FSLA	CPU	SRC[7:0]	PCI
0	0	100	100	33
0	1	133	100	33
1	0	200	100	33
1	1	166	100	33













SATA HDD CONN





CD-ROM CONN


Follow Adoi san suggest ODD: Master/HDD:Slave

FOXCONN			HON HAI Precision Ind. Co., Ltd.
Title			CCPBG - R&D Division
Size	Document Number	Rev	
A3	MS70-1-01	2.0	
Date:	Tuesday, August 22, 2006	Sheet	26 of 55






Touch Pad Board




CAP_LED# SCROLL_LOCK_LED# NUM_LOCK_LED#



MS LED


HDD_LED#



PVT

Ultra Yellow

POWER/SUSPEND LED



PVT


PVT

Ultra Amber /
Ultra Yellow Green

PVT


Ultra Yellow


BATTERY CHARGING LED#




www.vinafix.vn

FOXCONN		HON HAI Precision Ind. Co., Ltd.
Title LED/Touch PAD		CCPBG - R&D Division
Size A3	Document Number MS70-1-01	Rev 2.0
Date: Tuesday, August 22, 2006	Sheet 29	of 55







FOXCONN		HON HAI Precision Ind. Co., Ltd.	
Title		AUDIO(EXT MIC) 3/4	
Size	Document Number	Rev	
A3	MS70-1-01	2.0	
Date:	Tuesday, August 22, 2006	Sheet	35 of 55





EXPRESS CONN






MDC CONN.










MS STD/DUO CONN.




POWER BUTTON



LID Switch




EMI CAP

















USB CONN X 2

23,27,37,38 SUS_PWRGD_10MS



DVT





DCBATOUT

ALW_ON



System


+5VALW/5A

System

+3VALW/5.5A


+5VALW_LDO
+ECVCC
ALW_PWRGD

SUS_ON




+5VSUS/0.5A

RUN_ON




+5VRUN/3A

SUS_ON




+3VSUS/1.2A

RUN_ON



+3VRUN/4.3A


RUN_ON



+2_5VRUN/150mA

DCBATOUT

SUS_ON




+1_8VSUS/8.5A

+0_9VSUS/2A

DDRDIMM_VREF
DDR2_PWRGD

DCBATOUT

RUN_ON



+1_05VRUN/9.5A

+1_5VRUN/6.5A

RUN_PWRGD


SUS_ON



+8V For Load switch

DCBATOUT


IMVP_VR_ON




VHCORE/36A

CLK_EN#


IMVP_OK









Setting +1_5VRUN OCP trigger point to 10.5A

Setting +1_05VRUN OCP trigger point to 12.8A





Setting +1_8VSUS OCP trigger point to 11.6A





Discharge circuit for power-off





HISTORY (1)

(2006/04/25)

P.16 CN3 pin5 Add R515 0ohm for QDI LCD Panel doesn't support gamma correction issue.
P.17 Add VGA_CRT_DET# connect to U15 pin29 for Semi-PnP function fail issue.
P.20 U11 pin57 add R516 10Kohm pull down for LAN can't be recognized issue.
P.27 U15 pin29 add R513 10Kohm pull up for Semi-PnP function fail issue.
P.27 U15 pin12 add R514 100Kohm pull down for EC hardware strap pin.
P.27 U15 pin171 add C597 1000pF to ground for FAN can't be controlled issue.
P.31 R304 change from 4.7k to 10k for FAN can't be controlled issue.

(2006/05/03)

P.49 Add netname(IMVP_PHASEGD_1) on the right side of PR119 for application modification.
P.45 PC11, PC21, PC151, PR167 change from DNI to mount for DC_IN spike issue
P.45 PD4 pin1 and pin3 exchange for application modification
P.46 PR54 change from 100 ohm to 0 ohm for PU3 output abnormal issue
P.46 PR55 change from DNI to mount for can't boot up issue
P.47 PU4 pin3 change from GND to GND_SIGNAL_1D5V for application modification
P.48 PU5 pin5 change from GND to GND_SIGNAL_1D8V for application modification
P.49 Add PR169 NC_1M ohm for MAX8771 CCI issue
P.49 PC96, PC97, PC98, PC111, PC112, PC114 change from SANYO 2R5TPL330M9 to Panasonic EEF5X0D331XE for purchase difficult

(2006/05/04)

P.37 Add Q162(NC), R517, R518(NC) for Express card power sequence issue

(2006/05/15)

P.45 PR32 change from 22K_F to 23.2K_F for ACIN Vcls function trigger point correct to 3.4A
P.47 PR67 change from 8.2K_F to 4.7K_F for +1_05VRUN OCP trigger point correct to 12.8A
P.48 PR75 change from 6.8K_F to 5.6K_F for +1_8VSUS OCP trigger point correct to 11.6A
P.51 PR146 change from 51K_F to 46.4K_F for DCBATOUT OCP trigger point correct to 4.2A
P.51 PR150 change from 62K_F to 56K for PWRLIMIT# function trigger point correct to 3.6A
P.46 Delete PJ1, PJ2
P.47 Delete PJ3, PJ4, PJ5, PJ6
P.48 Delete PJ7, PJ8, PJ9

(2006/05/17)

P.45 Add PR41 10K_J_0402 and PQ13 2N7002 for preventing leakage current
P.45 PR17 change from 0.015_J 0805 to 0.015_F 1206 for application modification
P.46 PR55 change from 1K_J to 3.3K_J and PC55, PC57 change from 10u_25V X5R 1206 to 4.7u_10V X5R 0805 for reducing +ECVCC static current
P.47 PC71 change from mount to DNI for application modification
P.49 PR110 change from 20K_J to 0_J and PC102 change from DNI to mount for MAX8771 CCI issue
P.45 Delete PR19, PR28, PR33, PR35, PR37, PR38, PR39, PR40, PC31, PQ7, PQ10, PQ14, PQ16 For +ECVCC needed to work in battery only mode
P.51 Delete PD36, PD37 for +ECVCC needed to work in battery only mode
P.51 The net of VSOURCE (PQ43 pin3) change to DCBATOUT for +ECVCC needed to work in battery only mode
P.51 The net of BATT_EN (PD38 pin2) change to ALW_ON for +ECVCC needed to work in battery only mode

(2006/05/19)

P.13 C155 change from 2.2U_10V_Y_Y to 1000P_16V_K ; C159 change from 0.1U_16V_Y_Y to 1000P_50V_K for EMC DDR2 solution
P.14 C168 change from 2.2U_10V_Y_Y to 1000P_16V_K ; C172 change from 0.1U_16V_Y_Y to 1000P_50V_K for EMC DDR2 solution
P.15 C177,C179,C181,C191,C192,C196 change from 0.1U_16V_Y_Y to 1000P_50V_K for EMC DDR2 solution
P.39 C547,C548 change from 18P_50V_J_N to 22P_50V_J for PCI8402's Crystal issue
P.30 LED1 change from HT-110Y to HT-110UYG for LED color requirement
P.45 PCN1 change from MOLEX_53259-0229 to FOX_GS53020-00580-7F
P.45 PC11 change from 10U_25V_M_1206 to 10U_25V_M_B_1210 for purchase convenient
P.46 PC43,PC44,PC45 change from 10U_25V_M_B_1206 to 10U_25V_M_B_1210 for purchase convenient
P.47 PC58,PC59,PC62,PC63 change from 10U_25V_M_B_1206 to 10U_25V_M_B_1210 for purchase convenient
P.48 PC76,PC77 change from 10U_25V_M_B_1206 to 10U_25V_M_B_1210 for purchase convenient
P.48 PC86 change from 4.7U_10V_K_B_1206 to 4.7U_10V_K_0805 for purchase convenient
P.50 PC126,PC131 change from 10U_10V_M to 10U_6.3V_M for purchase convenient
P.50 PC127 change from 4.7U_25V_K_B_1206 to 4.7U_16V_K_0805 for purchase convenient

(2006/05/22)

P.32 CN21 change from FOXCONN_GB11060_0221_7F to FOXCONN_GB5RF060_1200_7F for ME's requirement
P.29 CN30,CN31 change from foxconn_gb11120_0221_7F to FOXCONN_GB5RF120_1200_7F for ME's requirement
P.29 CN31 change from mount to DNI for ME's requirement
P.50 PQ31,PQ34 change from DIODES,2N7002DW-7-F to CHENMKO,2N7002SPT for purchase convenient
P.51 PQ45 change from DIODES,2N7002DW-7-F to CHENMKO,2N7002SPT for purchase convenient
P.27 Q149 change from DIODES,2N7002DW-7-F to CHENMKO,2N7002SPT for purchase convenient

(2006/05/23)

P.47 PC62,PC63 change from 10U_25V_M_B_1210 to 10U_25V_M_B_1206 for ME limit of height
P.46 PC44,PC45 change from 10U_25V_M_B_1210 to 10U_25V_M_B_1206 for ME limit of height
P.46 Add PJ1,PJ2 for test request
P.47 Add PJ3,PJ4 for test request
P.48 Add PJ7,PJ9 for test request

(2006/05/24)

P.42 CN25,CN26(USB CONN) change from FOX_UB11193_C1301_4F to UB11193-C1308-4F for ME's requirement
P.17 CN5(VGA CONN) change from FOX_DZ11A91_MB221_4F to DZ11A91-MW223-4F for ME's requirement

(2006/05/25)

P.47 Add PJ6 for test request
P.26 CN8 footprint change from FOXCONN_LD2722H_S469 to FOXCONN_LD2722H_S469_MS70 for ME PAD request
P.32 C389 change from 22U_10V_Y_Y_1206 to 10U_10V_M_0805 and add C598 10U_10V_M_0805 for limit of ME
P.43 H1,H2,H3,H4 change from hole_c158d158n to HOLE_C148D148N for ME request
P.43 H7 change from hole_tsru144bsru177d98 to hole_trc321x287brud98 for ME request
P.43 H26 change from hole_c120d100 to hole_tsrlclbr413x343d98 for ME request
P.43 H23 change from hole_tc256brclD295d98_v1 to hole_tc256bs502x295d134_v1 for ME request
P.43 H25 change from hole_tc256brcu148d98 to hole_tc256bs295x384d134 for ME request
P.43 H5 change from hole_tc256bc315d98 to hole_tc256bc256d98 for ME request
P.43 H10 change from hole_tshrd144bc315d98 to hole_trc287x301bc256d98 for ME request
P.43 H9 change from hole_trcd144brcl177d98 to hole_trc287x321brcd98 for ME request
P.43 H12 change from hole_tc256bsrcu144d98 to hole_tc256bc287d98 for ME request

(2006/05/26)

P.42 CN25,CN26 change from FOXCONN_UB11193_C1308_4F to FOXCONN_UB11193_C1308_4F_HM for solder issue
P.43 H9 change from hole_trc287x321brcd98 to hole_trc287x256bshclD98 for ME request
P.17 D3 change from 16-CH500H4-0P00 to 16-SCS500V-4000 for purchase convenient
P.10 C119 change from 1C-2B30105-K000 to 1C-2B30475-K100 ; C120 change from 1C-2B20103-K001(0402) to 1C-2B30475-K100(0603) for +1_5VRUN_HMPLL noise issue
P.48 Add PJ8 for test request

(2006/06/01)

P.16 Add R519(0ohm 0402) for desinger set "LCDID3" to "0" by mistake.
P.49 PC102 change from mount to NC for application modification
P.46 PC52,PC53 change from 0.1U_16V_Y_Y(Y5V) to 0.1U_16V_M_B(X5R) for application modification
P.47 PC66,PC73 change from 0.1U_16V_Y_Y(Y5V) to 0.1U_16V_M_B(X5R) for application modification
P.49 PC99,PC113 change from 0.1U_16V_Y_Y(Y5V) to 0.1U_16V_M_B(X5R) for application modification
P.36 Q25 pin2 netname change from +5VRUN to +5VAMP
P.36 R376 pin2 netname change from GND to A_GND
P.36 Add U38,R520(NC) for SPK_MUTE_EN for Vista requirement
P.36 Add NET "SPK_MUTE_EN" from U38 pin2 to U15 pin99 for Vista requirement
P.40 Change U36,U37 from RT9702 to RT9703, Add R521-R524.
P.27 Delete Q149.

(2006/06/02)

P.16 R515,R519 change from mount to NC
P.36 Add R525(NC) for Audio mute option
P.49 Add PC152 for application modification
P.26 R510 change from mount to NC for application modification
P.22 R188 change from mount to NC for application modification

(2006/06/05)

P.49 PC92,PC108 change from NC to mount for design rating
P.40 U36,U37 change from RT9703 to RT9702, Del R521-R524 for RT9703 phase out issue
P.49 Add PC153 for solving audible noise
P.19 Add R526 for LAN application modification

(2006/06/06)

P.13 Add C599,C600(1000P_50V_K) ; C155 change from 1000P_16V_K to 2.2U_10V_Y_Y ; C159 change from 1000P_50V_K to 0.1U_16V_Y_Y for EMC solution
P.14 Add C601,C602(1000P_50V_K) ; C168 change from 1000P_16V_K to 2.2U_10V_Y_Y ; C172 change from 1000P_50V_K to 0.1U_16V_Y_Y for EMC solution
P.15 Add C603,C604(1000P_50V_K) ; C177,C179,C181,C191,C192,C196 change from 1000P_50V_K to 0.1U_16V_Y_Y for EMC solution
P.51 Add PD36,PD37 for application modification
P.19 C253 change form 0.1U_16V_M_B to 5P_50V_C ; C254 change from 5P_50V_C to 0.1U_16V_M_B ; Add L58 ; Del R526 for LAN application modification

FOXCONN			HON HAI Precision Ind. Co., Ltd.
History (1)			CCPBG - R&D Division
File	Document Number	Rev	
Size	MS70-1-01	2.0	
C			
Date:	Tuesday, August 22, 2006	Sheet	52 of 55

HISTORY (2)

(2006/06/07)
P.26 R245 change from NC to mount for application modification

(2006/06/13)
P.33 R325 change from mount to NC for acoustic noise.
P.36 U38 change from 74AHC1G08GW to 74AHCT1G08GW for Vih can't meet EC spec.

PVT

(2006/07/12)
P.47 Change PC68, PC70 from mount to NC for TPS51124 OVP issue.
P.27 Add R526 (1K ohm) series on ALW_ON net to prevent EC damage issue.
P.46 Delete PJ1, PJ2
P.47 Delete PJ3, PJ4, PJ6
P.48 Delete PJ7, PJ8, PJ9
P.32 F1,R320,R321,L32,C598,C389,C390,C391,CN21 change from mount to NC for cancel Oide function
P.37 U33 change from 15-TPS2231-0000(24pin) to 15-TPS2231-0002(20pin) for purchase convenient
P.40 U36,U37 change from 15-RT9702A-0000 to 15-TPS2055-0000 ;
Add R527,R528 for MS_PWR_CTRL and SD_PWR_CTRL are recognized to be high level by accident

(2006/07/20)
P.26 CN9 vendor part number change from QT8H0506-13T3R-7F to QT8H0506-13T3R-4F
for packing type change.
P.49 PC153 change from 1C-10X0107-M403 to 1C-1XX0107-M400 for purchase convenient.
P.29 Delete CN31 for touch pad application modification.
P.22 R195 change from 47ohm to 0ohm ; C293 change from NC to mount for EMI solution.
P.29 LED6 change from 16-HT210DY-G000 to 16-HT210UD-UY00 for ME brightness issue.
LED5,LED7 change from 16-HT110Y0-0000 to 16-HT110UY-0000 for ME brightness issue.

(2006/07/21)
P.26 Add D22(NC) for ESD solution
P.30 R301 change from 120ohm to 47ohm for ME brightness issue

(2006/07/25)
P.30 C365 change from NC to mount for WLAN power ripple noise issue
P.26 Add VR1 for ESD solution
P.29 Add VR2,VR3(NC) for ESD solution
P.41 Add VR4,VR5(NC) for ESD solution

(2006/07/28)
P.29 Q155 change from 17-CHDTC14-4E01 to 17-2N70020-0000 for ME brightness issue.

(2006/07/31)
P.30 R301 change from 47ohm to 120ohm (LED1 is 10mA) for ME brightness issue
P.29 R418 change from 47ohm to 62ohm (LED5 is 18.75mA) for ME brightness issue
P.29 R424 change from 47ohm to 62ohm (LED6 is 19.5mA)
R425 change from 47ohm to 120ohm (LED6 is 10mA)for ME brightness issue
P.29 R426 change from 47ohm to 62ohm (LED7 is 18.9mA)

(2006/08/01)
P.31 Q17 change from 17-ME2301T-1000 to 17-S12301B-DS00 for Fan rotational speed issue

-----PVT schematic released

(2006/08/07)
P.45 PC42 change from 1C-2B30104-K000(0.1u) to 1C-2B30224-K000(0.22u)
and mount PC42 for solving AC_OFF_3# abnormal issue
P.34 R350 change from 6.2kohm to 6.98kohm for adjust the gain of speaker amp
P.26 VR1 change from mount to NC ; D22 change from NC to mount for purchase convenient.
P.29 R418,R426 change from 62ohm to 120ohm for LED brightness issue

(2006/08/13)
P.45 PR3 change from 1kohm to 20kohm for power circuit design improvement plan
which is DC_IN OVP circuit.

-----PVT SMT

MP

(2006/08/16)
P.23 Add D23 from IMVP_PWRGD to ALW_PWRGD for RTC stop issue backup (D23 is NC)
Add D24 from PM_RSMRST#(A3602) to ALW_PWRGD for RTC stop issue backup (D24 is NC)

(2006/08/17)
P.40 Add Q163,Q164,R529,F2(MS_PWR) for purchase convenient
Add Q165,Q166,R530,F3(SD_PWR) for purchase convenient

(2006/08/18)
P.40 R392,R395 change from 1Mohm to 100Kohm
F2,F3 move to pin3 side of Q163,Q165
P.40 Q163,Q165 change from PMBT2907A(PNP) to SI2301BDS-T1-E3(P-MOS)
R529,R530 change from 1.5kohm to 1kohm
Add R531,R532 4.7kohm
P.23 R221 change from 100ohm to 1kohm
D23,D24 change from BAS316PT to SCS500V-40-LF
D23,D24 change from NC to mount for RTC stop issue

(2006/08/23)
P.40 Q163,Q165 change from VISHAY_SI2301BDS-T1-E3 to Philips_PMV65XP for purchase convenient.